



SmartPro 120V 700VA 450W Medical-Grade Line-Interactive Tower UPS with 4 Outlets, Full Isolation, USB, DB9

MODEL NUMBER: SMART700HG





Provides UL 60601-1 compliant, medical-grade 700VA/450W power backup, ideal for use in patient-care vicinities. The built-in isolation transformer offers full isolation while maintaining AC surge protection in all modes.

Description

SMART700HG medical-grade UPS system provides dependable battery backup and is fully compliant with UL 60601-1 regulations when plugged into a hospital-grade outlet, making it ideal for use in patient-care vicinities. The 700VA/450W capacity provides up to 42 minutes of runtime for a half load, or 18 minutes for a full load so you can work through short power failures and perform an orderly system shutdown in a prolonged blackout.

Built-in line-interactive voltage regulation corrects brownouts as low as 81V and overvoltages as high as 143V to normal 120V nominal output, without drawing battery power. The SMART700HG's built-in isolation transformer with Faraday shield offers full isolation and removes common mode noise while maintaining full AC surge suppression in all modes.

This UPS system features four NEMA 5-15R-HG hospital-grade outlets and has a hospital-grade NEMA 5-15P-HG plug with a six-foot cord for flexibility in placement. All four outlets provide both backup protection and surge protection, rated to 480 joules.

The SMART700HG also features diagnostic LEDs, as well as a USB port and a DB9 serial port that work with free downloadable PowerAlert® software for safe, unattended system shutdown and file saves in the event of a prolonged power failure.

Application Usage

This UPS contains a lead acid battery designed to be connected continuously to an AC power source, except during brief power outages. It is not intended for frequent charge/discharge cycles, such as mobile cart applications where the UPS is often disconnected from the power source. Using the SMART700HG in this type of application will void the battery warranty. For mobile applications, we recommend the SMART700HGL with lithium iron phosphate (LiFePo4) battery.

Features

Provides Ideal UPS Backup in Healthcare Facilities

- Compliant with UL 60601-1 standards for use in patient-care vicinities, when plugged into a hospitalgrade outlet
- Built-in isolation transformer with Faraday shield offers full isolation and removes common mode noise
- Hospital-grade plug with 6 ft. cord provides flexibility in placement so healthcare workers can focus on

Highlights

- Supports a half load up to 42 minutes; full load up to 18 minutes
- Four hospital-grade outlets and hospital-grade plug
- 480 joule surge suppression rating protects connected equipment
- Alarm mute/alarm quiet control is ideal for use around patients
- Approved for use within the Patient Care Vicinity
- Approved to EN60601-1-2:2015 and IEC60601-1-2:2014, 4th Edition

Package Includes

- SMART700HG 700VA/450W Medical-Grade Tower UPS System
- USB monitoring cable, 6 ft.
- DB9 serial monitoring cable, 6 ft.
- Owner's Manual





treating the patient

Battery Backup and Full Surge Protection

- 42 minutes runtime for half load (225W); 18 minutes for full load (450W)
- All four hospital-grade outlets provide surge protection rated to 480 joules
- EMI/RFI noise filtering ensures equipment runs smoothly without line noise interference
- Resistant to electrostatic discharge

LEDs and Audible Alarms Keep You Aware of Power Status

- Indicator lights on the front of the unit show you when the UPS is on and supplying utility power, when
 operating in voltage correction mode or in battery mode, relative load level and low-battery warning
- Audible alarms alert you to power failure, overload and low battery conditions; the alarm's mute/quiet
 mode ensures patients are not disturbed

Saves Your Files, Even When You're Away

- Works with PowerAlert software (available as a free download) to enable safe, unattended system shutdown and files saves during prolonged power failures
- Connects to your computer via either the DB9 port or USB port

Specifications

OVERVIEW		
UPC Code	037332095107	
UPS Type	Line-Interactive	
INPUT		
Input Phase	Single-Phase	
Rated input current (Maximum Load)	5.5A	
Nominal Input Voltage(s) Supported	120V AC	
UPS Input Connection Type	5-15P-HG	
Input Circuit Breakers	10A	
UPS Input Cord Length (ft.)	6	
UPS Input Cord Length (m)	1.8	
Recommended Electrical Service	15A 120V	
Input Cord Length (ft.)	6	
Input Cord Length (m)	1.83	
OUTPUT		
Output Capacity (VA)	700	
Output Capacity (kVA)	0.7	
Output Capacity (Watts)	450	





Support Spacing (NY) Power Factor 0.6 Frequency Compatibility 60 Hz Curput Voltage Regulation (Line 18%, +8% Curput Voltage Regulation (Eattery Mobile) Curput Voltage Regulation (Battery 15%) Mobile (Statery Mobile) Curput Voltage Regulation (Battery 15%) Mobile (Statery Mobile) Curput AC Waveform (AC Mode) Sine wave Curput AC Waveform (Rattery Mobile) Curput Receptacle Details Hospital grade output receptacles Curput AC Waveform (Rattery Mobile) Curput AC Waveform (Rattery Mobile) Curput Receptacles (4) 5-15R Individually Controllable Load Banks No BATTERY Battery Battery Type Valve Regulated Lead Acid (VRLA) Runtine Full Load (min.) 15 min. (450W) Runtine Full Load (min.) 16 min. (450W) Expandable Runtine DC System Voltage (VDC) 36 Battery Recharge Rate (Included) Battery Rechar	Output Capacity (kW)	0.45	
Frequency Compatibility 0 Hz Output Yoltage Regulation (Line 18%, +8% Output Yoltage Regulation (Eattery Mode) 150 (V.5%) Output Receptacle Details Hooptal grade output receptacles Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery PwW sine wave Output AC Waveform (Battery PwW sine wave Output AC Waveform (Battery PwW sine wave Output Receptacles (4) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Vave Regulated Lead Acid (VRLA) Runtime Full Load (min.) 18 min. (450W) Runtime Hall Load (min.) 42 min. (229W) Expandable Runtime No Ox System Voltage (NCC) 35 Battery Recharge Rate (Included Batter) Less than 4 hours from 10% to 90% Battery Recharge Rate (Included Batter) Recasts Rate (Included Batter) Recharge Rate (Included Batter) Recharge Rate (Included Cand Batter) Recasts Rate (Included Cand Batter) Recharge Rate (Included Cand Cand Cand Cand Cand Cand Cand Can			
Output Voltage Regulation (Line Mode) -18%, +8% Output Notage Regulation (Battery Mode) 115V (+/-5%) Output Receptacle Details Hospital grade output receptacles Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery Mode) PWM sine wave Output AC Waveform (Battery Mode) PWM sine wave Output Receptacles (4) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 18 min. (450W) Runtime Full Load (min.) 42 min. (25W) Expandable Runtime No DC System Voltage (VDC) 36 Battery Recharge Rate (Included Batteries) Battery Recharge Rate (Included Batteries) Battery Recharge Rate (Included Batteries) Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages b			
Mode) 1 15 175 175 175 175 175 175 175 175 17		00 HZ	
Mode) Mode (No. 10.00) Output Receptacle Details Hospital grade output receptacles Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery Mode) PVM sine wave Output Receptacles (4) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 18 min. (450W) Runtime Full Load (min.) 42 min. (255W) Expandable Runtime No Oc System Voltage (VDC) 36 Battery Recharge Rate (Included Batteries) Less than 4 hours from 10% to 90% Battery Access Battery access door Internal UPS Replacement Battery Replacement Description RBC36SLT Battery Replacement Description Hot-swappable, user replaceable batteries Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% User InterrACE, ALERTS & Correction <td></td> <td>-18%, +8%</td>		-18%, +8%	
Output AC Waveform (AC Mode) Sine wave Output AC Waveform (Battery Mode) PWM sine wave Nominal Output Voltage(s) 115V: 120V Output Receptacles (4) 5-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 18 min. (450W) Runtime Full Load (min.) 42 min. (225W) Expandable Runtime No DC System Voltage (VDC) 36 Battery Recharge Rate (Included Batteries) Less than 4 hours from 10% to 90% Battery Access Battery Access Internal UPS Replacement Battery Access Battery Access Hours are replaceable batteries Vol.TAGE REGULATION Vol. (AVR.) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% VSER INTERFACE, ALERTS & Cover-Lial alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status	Output Voltage Regulation (Battery Mode)	115V (+/- 5%)	
Output AC Waveform (Battery Mode) PWM sine wave Nominal Output Voltage(s) Supported 115V; 120V Output Receptacles (4) 6-15R Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 18 min. (450W) Runtime Half Load (min.) 42 min. (225W) Expandable Runtime No DC System Voltage (VDC) 36 Battery Recharge Rate (Included Stateries) Less than 4 hours from 10% to 90% Battery Access Battery access door Internal UPS Replacement Battery acress door RBC36SLT Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Hot-swappable, user replaceable batteries Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% User INTERFACE, ALERTS & Cottles control off/on power status and alarm-cancel switch; once silenced, alarm will re-so	Output Receptacle Details	Hospital grade output receptacles	
Nominal Output Voltage(s) Supported Voltage(s) Voltage(s) Voltage(s) Volve Receptacles Individually Controllable Load Banks No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) Valve Regulated Lead Acid (VRLA) Runtime Half Load (min.) Valve Regulated Lead Acid (VRLA) Runtime Half Load (min.) Valve Regulated Lead Acid (VRLA) Runtime Half Load (min.) Valve Regulated Lead Acid (VRLA) Runtime Half Load (min.) Voltage Recharge Rate (Included Leas Acid (VRLA) Voltage Recharge Rate (Included Leas than 4 hours from 10% to 90% Battery Recharge Rate (Included Leas than 4 hours from 10% to 90% Battery Recharge Rate (Included Leas than 4 hours from 10% to 90% Battery Recharge Rate (Included Leas than 4 hours from 10% to 90% Battery Recharge Rate (Included Leas than 4 hours from 10% to 90% Battery Recharge Rate (Included Leas than 4 hours from 10% to 90% Battery Recharge Rate (Included Leas than 4 hours from 10% to 90% Battery Recharge Rate (Included Leas than 4 hours from 10% to 90% Battery Recharge Rate (Included Leas than 4 hours from 10% to 90% Battery Replacement Description Holt-swappable, user replaceable batteries Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Patterny status Adible Alarm Adible Alarm Adible alarm indicates power-failure, overload and low-battery conditions	Output AC Waveform (AC Mode)	Sine wave	
Supported (4) 5-15R Individually Controllable Load Banks (No BATTERY Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 18 min. (450W) Runtime Full Load (min.) 42 min. (225W) Expandable Runtime No DC System Voltage (VDC) 36 Battery Recharge Rate (Included Battery's Recharge Rate (Included Least Acid valve from 10% to 90% Battery Recharge Rate (Included Least Acid valve from 10% to 90% Battery Recharge Rate (Included Least han 4 hours from 10% to 90% Battery Recharge Rate full valve from 10% to 90% Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% VSER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Battery status Audible alarm indicates power-failure, overload and low-battery conditions	Output AC Waveform (Battery Mode)	PWM sine wave	
BATTERY Satiety Type	Nominal Output Voltage(s) Supported	115V; 120V	
Battery Type Valve Regulated Lead Acid (VRLA) Runtime Full Load (min.) 18 min. (450W) Runtime Half Load (min.) 42 min. (225W) Expandable Runtime No DC System Voltage (VDC) 36 Battery Recharge Rate (Included Battery) Battery Access Battery access door Internal UPS Replacement Battery Cartridge Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control offron power status and alarm-cancel/self-test operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible Alarm indicates power-failure, overload and low-battery conditions	Output Receptacles	(4) 5-15R	
Runtime Full Load (min.) Runtime Full Load (min.) Runtime Half Load (min.) Runtime Half Load (min.) Expandable Runtime No DC System Voltage (VDC) Battery Recharge Rate (Included Battery Carridge Runtime Battery Recharge Rate (Included Battery) Recharge Replacement Battery Carridge Recharge Replacement Battery Carridge Recharge Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTOLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible Alarm Audible Alarm indicates power-failure, overload and low-battery conditions	Individually Controllable Load Banks	No	
Runtime Full Load (min.) 18 min. (450W) Runtime Half Load (min.) 42 min. (225W) Expandable Runtime No DC System Voltage (VDC) 36 Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery Carridge Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	BATTERY		
Runtime Half Load (min.) Expandable Runtime No DC System Voltage (VDC) Battery Recharge Rate (Included Battery access door Internal UPS Replacement Battery Access Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTOLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Audible Alarm Audible Alarm indicates power-failure, overload and low-battery conditions	Battery Type	Valve Regulated Lead Acid (VRLA)	
Expandable Runtime No DC System Voltage (VDC) 36 Battery Recharge Rate (Included Battery access than 4 hours from 10% to 90% Battery Access Battery access door Internal UPS Replacement Battery ReCartridge Regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTOLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible Alarm indicates power-failure, overload and low-battery conditions	Runtime Full Load (min.)	18 min. (450W)	
Battery Recharge Rate (Included Less than 4 hours from 10% to 90% Battery Access Battery access door Internal UPS Replacement Battery Recharge Regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Audible Alarm Audible Alarm indicates power-failure, overload and low-battery conditions	Runtime Half Load (min.)	42 min. (225W)	
Battery Recharge Rate (Included Batteries) Battery Access Battery access door Internal UPS Replacement Battery Cartridge Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate lowbattery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	Expandable Runtime	No	
Battery Access Battery access door Internal UPS Replacement Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	DC System Voltage (VDC)	36	
Internal UPS Replacement Battery Cartridge Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	Battery Recharge Rate (Included Batteries)	Less than 4 hours from 10% to 90%	
Battery Replacement Description Hot-swappable, user replaceable batteries VOLTAGE REGULATION Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	Battery Access	Battery access door	
Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	Internal UPS Replacement Battery Cartridge	RBC36SLT	
Voltage Regulation Description Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143 Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	Battery Replacement Description	Hot-swappable, user replaceable batteries	
Overvoltage Correction Input voltages between 126 and 143 are reduced by 9% Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	VOLTAGE REGULATION		
Undervoltage Correction Input voltages between 96 and 106 are boosted by 10% Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	Voltage Regulation Description	Automatic voltage regulation (AVR) maintains line power operation with an input voltage range of 81 to 143	
Severe Undervoltage Correction Input voltages between 81 and 95 are boosted by 21% USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	Overvoltage Correction	Input voltages between 126 and 143 are reduced by 9%	
USER INTERFACE, ALERTS & CONTROLS Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	Undervoltage Correction	Input voltages between 96 and 106 are boosted by 10%	
Switches 2 Switches control off/on power status and alarm-cancel/self-test operation Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	Severe Undervoltage Correction	Input voltages between 81 and 95 are boosted by 21%	
Alarm Cancel Operation Power-fail alarm can be silenced using alarm-cancel switch; once silenced, alarm will re-sound to indicate low-battery status Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	USER INTERFACE, ALERTS & CONTROLS		
Audible Alarm Audible alarm indicates power-failure, overload and low-battery conditions	Switches	2 Switches control off/on power status and alarm-cancel/self-test operation	
	Alarm Cancel Operation		
LED Indicators 5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status	Audible Alarm	Audible alarm indicates power-failure, overload and low-battery conditions	
	LED Indicators	5 LEDs indicate line power, battery power, overload, voltage regulation and battery low/replace status	





ISOLATION		
Output Isolation Transformer	Hospital grade load isolation transformer	
Leakage Current	Equal to 100 microamps	
SURGE / NOISE SUPPRESSION		
UPS AC Suppression Joule Rating	480	
UPS AC Suppression Response Time	Instantaneous	
EMI / RFI AC Noise Suppression	Yes	
AC Suppression Joule Rating	480	
AC Suppression Response Time	Instantaneous	
PHYSICAL		
Primary Form Factor	Tower	
Rack Height	OU	
Cooling Method	Fan	
Installation Form Factors Supported with Optional Accessories	Wallmount (UPSWM - tower mounting kit)	
Primary UPS Depth (mm)	229	
Primary UPS Height (mm)	325	
Primary UPS Width (mm)	191	
Shipping Dimensions (hwd / in.)	17.00 x 11.20 x 13.00	
Shipping Dimensions (hwd / cm)	43.18 x 28.45 x 33.02	
Shipping Weight (lbs.)	45.30	
Shipping Weight (kg)	20.55	
UPS Housing Material	PVC	
UPS Power Module Dimensions (hwd, cm)	32.51 x 19.05 x 22.86	
UPS Power Module Dimensions (hwd, in.)	12.8 x 7.5 x 9	
UPS Power Module Weight (kg)	20.05	
UPS Power Module Weight (lbs.)	44.2	
Unit Dimensions (hwd / in.)	12.500 x 7.500 x 9.500	
Unit Weight (lbs.)	44.200	
Unit Weight (kg)	20.05	
ENVIRONMENTAL		
Operating Temperature Range	32° to 104°F (0° to 40°C)	
Storage Temperature Range	5° to 122°F (-15° to 50°C)	





Relative Humidity	0 to 95%, non-condensing	
AC Mode BTU / Hr. (Full Load)	97.7	
AC Mode Efficiency Rating (100% Load)	94%	
Battery Mode Heat Dissipation (BTU/Hr) @ Full Load	189.1	
Battery Mode Heat Dissipation (BTU/Hr) @ Half Load	114.3	
COMMUNICATIONS		
Network Monitoring Port Description	Supports detailed monitoring of UPS and site power conditions	
PowerAlert Software	For local monitoring via the UPS's built-in communication ports, download PowerAlert software at https://tripplite.eaton.com/products/power-alert	
Communications Cable	USB and DB9 serial cabling included	
Network Management Card Description	Network management not supported	
Communications Interface	USB; DB9 Serial	
LINE / BATTERY TRANSFER		
Transfer Time	2-4 milliseconds	
Low Voltage Transfer to Battery Power (Setpoint)	81	
High Voltage Transfer to Battery Power (Setpoint)	143	
FEATURES & SPECIFICATIONS		
Cold Start (Startup in Battery Mode During a Power Failure)	Cold-start operation supported	
High Availability UPS Features	Hot swappable batteries; Surge/noise protection	
Green Energy-Saving Features	Greater than 95% efficiency - GREEN UPS	
Grounding Details	Grounding lug	
APPLICATIONS		
UPS Applications	Hospital/Medical	
STANDARDS & COMPLIANCE		
Product Certifications	CSA (Canada); UL 1778; UL 60601-1; NOM (Mexico)	
Product Compliance	RoHS; FCC Part 15 Class A (USA)	
WARRANTY & SUPPORT		
Product Warranty Period (Worldwide)	2-year limited warranty	





1000 Eaton Boulevard Cleveland, OH 44122 United States https://tripplite.eaton.com © 2024 Eaton. All Rights Reserved. Eaton is a registered trademark. All other trademarks are the property of their respective owners.